

» Smoke Panel – VCS-1



» VCS-1

- Single Zone 10Amp 24V dc Control Panel.
- 72-hour battery back-up on mains failure.
- 300mm x 200mm x 150mm IP65 steel enclosure.
- Sealed lead acid batteries.
- Auto cut off to protect batteries.
- Relay to provide volt free fault indication.
- Close-Auto-Open Function. Front of panel keyswitch to control open, close function of actuators/vents (full override priority).
- Facility to connect smoke heads to automatically reset once smoke has cleared.
- Variable opening of vents option available as special order
- Multi-Zone versions available by special order.

Inputs for:

- Fire alarm signal
- Break glass call points
- Smoke detectors
- Heat detectors
- BMS
- Fireman's override switch
- Thermostat
- Rain sensor
- Wind sensor (subject to special order)



VCS – Battery